

Optical Line Terminals

LTP-8X, LTP-4X

Application to the user manual

OLT configuration and monitoring via SNMP

Firmware version 3.46.0

Contents

1	Operation with ONT	6
1.1	ONT Configuration	6
1.1.1	Addition	7
1.1.2	Editing	7
1.1.3	ONT deletion	9
1.1.4	ONT replacement	10
1.1.5	Reconfiguration	10
1.1.6	Reboot	10
1.1.7	Reset to the default settings	10
1.1.8	Deactivation	11
1.1.9	Activation	11
1.1.10	ONT firmware updating via OMCI protocol	11
1.2	Requests	12
1.2.1	Common ONT state	12
1.2.2	PPP session state	12
1.2.3	MAC table	13
1.2.4	IGMP group table	14
1.2.5	ONT connection log	14
1.2.6	ONT timers	15
1.2.7	Counter reset on ONT	20
1.2.8	GPON port counter reset	21
2	OLT configuration	22
2.1	Applying and confirming configuration	22
2.1.1	Save configuration into non-volatile memory	22
2.1.2	Reread configuration from non-volatile memory	22
2.2	VLAN Configuration	22
2.2.1	Adding a VLAN	22
2.2.2	Editing a VLAN	23
2.2.3	Deleting a VLAN	24
2.2.4	Requesting the list of VLANs and configuring a specific VLAN	24
2.3	Terminal VLAN Configuration	25
2.3.1	Adding Terminal VLAN	25
2.3.2	Editing Terminal VLAN	25
2.3.3	Deleting Terminal VLAN	25
2.3.4	Requesting the list of Terminal VLANs and configuring a specific Terminal VLAN	26
2.4	IGMP/MLD Configuration	27

2.4.1	Global settings for enabling IGMP/MLD Snooping.....	27
2.4.2	IGMP Snooping and VLAN Querier configuration.....	27
2.5	OLT, ONT profiles configuration	28
2.5.1	Address-table	28
2.5.2	Cross-connect	29
2.5.3	DBA	30
2.5.4	Ports	32
2.6	PON channels.....	34
2.6.1	Enabling/disabling PON channels	34
2.6.2	Reconfiguration.....	34
2.6.3	Unknown multicast forwarding enabling.....	35
2.6.4	Viewing counters	35
2.7	Switch interfaces configuration.....	36
2.7.1	PVID assigning	36
2.7.2	Bridging configuration	36
2.7.3	Port Channel configuration	36
2.7.4	Multicast loopback configuration.....	37
2.8	IP Source Guard configuration.....	38
2.8.1	Operating mode enabling and configuration	38
2.8.2	IP Source Guard Bind configuration	38
2.8.3	IP Source Guard Ignored Vlan configuration.....	39
3	Operations for uploading/downloading OLT firmware (TFTP/HTTP).....	40
3.1	OLT firmware download	40
3.2	Current LTP firmware request.....	40
3.3	Reboot	40
3.4	ONT firmware.....	41
3.4.1	Firmware downloading	41
3.4.2	Requesting a list of downloaded firmware files	41
3.4.3	Deleting uploaded firmware	42
3.5	Configuration uploading/downloading.....	42
3.5.1	Backup configuration uploading.....	42
3.5.2	Backup configuration downloading.....	42
4	OLT monitoring	44
4.1	Active alarms	44
4.2	LTP general information.....	44
4.3	Power supply.....	44
4.4	Port and PON channel state.....	45
4.5	MAC Table	45

4.6	Multicast.....	46
4.7	PPPoE sessions	46
4.8	Licensing information.....	47
5	The list of changes	48

Notes and warnings

- ⚠ Notes contain important information, tips or recommendations on device operation and configuration.
- ❗ Warnings are used to inform the user about situations that may cause harm to a software and hardware complex, lead to malfunction or data loss.

1 Operation with ONT

⚠ The correspondence between parameter names and numeric OIDs is given in the MIB files.

If the command has ONT serial number (dec_serial), this serial number should be specified by 8 decimal numbers separated by dots.

Examples:

Serial number	SNMP command parameter
ELTX24A80012	69.76.84.88.36.168.0.18
45-4C-54-58-00-00-00-01	69.76.84.88.0.0.0.1

ONT profiles are specified by the profile index for corresponding OID of the ONT configuration. To get profile index using its name, use the following profile tables.

Profile type	Table
Management	Itp8xONTManagementProfileTable
Ports	Itp8xONTPortsProfileTable
Shaping	Itp8xONTShapingProfileTable
Scripting	Itp8xONTScriptingProfileTable
DBA	Itp8xONTAllocProfileTable
Cross-connect	Itp8xONTCrossConnectProfileTable

To set *unassigned* value, if it is allowed, number 65535 will be transmitted instead profile index.

1.1 ONT Configuration

ONT is configured by the following tables:

- Itp8xONTConfigTable – general parameters;
- Itp8xONTCustomCrossConnectTable – custom parameters;
- Itp8xONTFullServicesConfigTable – Cross-Connect and DBA profiles;
- Itp8xONTSelectiveTunnelTable – selective-tunnel uvids.

1.1.1 Addition

When adding ONT It is necessary to specify serial number, gpon-port number and ONT ID.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTConfigRowStatus.1.8.<dec_serial> i 4
ltp8xONTConfigChannel.1.8.<dec_serial> u <gpon_port>
ltp8xONTConfigID.1.8.<dec_serial> u <ont_id>
```

Where:

- <gpon_port> – the real value of the port number;

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTConfigRowStatus.1.8.69.76.84.88.36.168.0.18 i 4
ltp8xONTConfigChannel.1.8.69.76.84.88.36.168.0.18 u 6
ltp8xONTConfigID.1.8.69.76.84.88.36.168.0.18 u 0
```

This command creates ONT 6/0 with serial number ELTX24A80012.

1.1.2 Editing

1.1.2.1 ONT General Parameters

General parameters of ONT are configured by using *ltp8xONTConfigTable*.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> <parameter_oid_1>.1.8.<dec_serial> <par1_type> <par1_value>
<parameter_oid_2>.1.8.<dec_serial> <par2_type> <par2_value>
.....
<parameter_oid_N>.1.8.<dec_serial> <parN_type> <parN_value>
```

Where:

- <parameter_oid_N> – the names of specific MIB parameters;
- <parN_type> – value type of a parameter;
- <parN_value> – parameter value.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTConfigDescription.1.8.69.76.84.88.36.168.0.18 s
"ont_description"
ltp8xONTConfigManagementProfile.1.8.69.76.84.88.36.168.0.18 u 1
ltp8xONTConfigFecUp.1.8.69.76.84.88.36.168.0.18 i 1
```

This command sets the *description* value, specifies Management profile, and enables error correction for ONT with serial number ELTX24A80012.

1.1.2.2 Cross-Connect and DBA profiles

Cross-Connect and DBA profiles are configured by using *ltp8xONTFullServicesConfigTable*. Similarly to the custom parameters, additional index (service number) and value increased by 1 should be specified.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTFullServicesConfigCrossConnectProfile.1.8.<dec_serial>.<service> u <value>
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTFullServicesConfigCrossConnectProfile.1.8.69.76.84.88.36.168.0.18.8 u 1
ltp8xONTFullServicesConfigDBAProfile.1.8.69.76.84.88.36.168.0.18.8 u 2
```

For ONT with serial number ELTX24A80012, this command sets Cross-Connect profile with index 1, and DBA profile with index 2 for service 7.

1.1.2.3 Custom Cross-Connect parameters

Custom Cross-Connect parameters are configured by using *ltp8xONTCustomCrossConnectTable*. Introduces additional index (service number) including service number increased by 1.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTCustomCrossConnectEnabled.1.8.<dec_serial>.<service> i <value>
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTCustomCrossConnectEnabled.1.8.69.76.84.88.36.168.0.18.3 i 1
ltp8xONTCustomCrossConnectVID.1.8.69.76.84.88.36.168.0.18.3 i 100
ltp8xONTCustomCrossConnectCOS.1.8.69.76.84.88.36.168.0.18.3 i 1
ltp8xONTCustomCrossConnectSVID.1.8.69.76.84.88.36.168.0.18.3 i 200
```

For ONT with serial number ELTX24A80012, this command activates Custom Cross Connect parameters for service 2 and sets values cvid=100, svid=200, cos=1.

1.1.2.4 Selective-tunnel uvids

Selective-tunnel uvids are configured by using *ltp8xONTSelectiveTunnelTable*. In addition to the service number, an index should be entered – the selective-tunnel uvid number. Index takes the values from 1 to 42. The indexes of the assigned uvid must follow sequentially without order interruption. For example, if uvid are determined with indexes 1 and 2 the next assigned uvid must have index 3.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTSelectiveTunnelUVID.1.8.<dec_serial>.<service>.<uvid_id> i
<SelectiveTunnelUVID_value>
```

Where:

- <SelectiveTunnelUVID_value> – selective-tunnel uvid value.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTSelectiveTunnelUVID.1.8.69.76.84.88.36.168.0.18.8.1
i 200
```

For ONT with serial number ELTX24A80012, this command adds selective-tunnel uvid=200 for service 7.

1.1.2.5 PoE management on ONT ports

PoE management on ONT ports is configured via ltp8xOntConfigUniPortTable table.

Command format:

```
snmpset -v2c -c <rw_community><ipaddr><parameter_oid_1>.
1.8.<dec_serial>.<port_number><par1_type><par1_value><parameter_oid_2>.
1.8.<dec_serial>.<port_number><par2_type><par2_value>
.....
<parameter_oid_N>.1.8.<dec_serial>.<port_number><parN_type><parN_value>
```

To enable PoE on port, do the following:

```
snmpset -v2c -c <rw_community><ipaddr>ltp8xOntConfigUniPortRowStatus.1.8.<dec_serial>.<port_number>
i 4
```

To disable PoE on port, do the following:

```
snmpset -v2c -c <rw_community><ipaddr>ltp8xOntConfigUniPortRowStatus.1.8.<dec_serial>.<port_number>
i 6
```

Where:

- <parameter_oid_N> – names of specific parameters in MIB;
- <parN_type> – parameter value type;
- <parN_value> – parameter value;
- <port_number> – port number.

Example:

```
snmpset -v2c -c private 192.168.10.151
ltp8xOntConfigUniPortRowStatus.1.8.69.76.84.88.130.0.0.2.1 i 4
ltp8xONTPrtsUNIPoeEnable.1.8.69.76.84.88.130.0.0.2.1 i 1
ltp8xONTPortsUNIPoeClassControl.1.8.69.76.84.88.130.0.0.2.1 u 1
ltp8xONTPortsUNIPoePowerPriority.1.8.69.76.84.88.130.0.0.2.1 u 3
```

1.1.3 ONT deletion

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTConfigRowStatus.1.8.<dec_serial> i 6
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTConfigRowStatus.1.8.69.76.84.88.36.168.0.18 i 6
```

This command deletes ONT configuration with serial number ELTX24A80012.

1.1.4 ONT replacement

ONT can be changed by using subsequent commands for deleting and creating configurations with new parameters.

1.1.5 Reconfiguration

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTStateReconfigure.1.8.<dec_serial> u 1
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTStateReconfigure.1.8.69.76.84.88.36.168.0.18 u 1
```

1.1.6 Reboot

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTStateReset.1.8.<dec_serial> u 1
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTStateReset.1.8.69.76.84.88.36.168.0.18 u 1
```

1.1.7 Reset to the default settings

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTStateResetToDefaults.1.8.<dec_serial> u 1
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTStateResetToDefaults.1.8.69.76.84.88.36.168.0.18 u 1
```

1.1.8 Deactivation

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xONTDisableONTSerial.0 x
<hex_serial> ltp8xONTDisableChannel.0 u <gpon_port>
ltp8xONTDisableActionDisable.0 u 1
```

Where:

- <hex_serial> – serial number in hex format;
- <gpon_port> – the real value of the port number.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTDisableONTSerial.0 x
"454C545824A80012" ltp8xONTDisableChannel.0 u 6
ltp8xONTDisableActionDisable.0 u 1
```

The command performs ONT ELTX24A80012 deactivation on channel 6.

1.1.9 Activation

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xONTDisableONTSerial.0 x
<hex_serial> ltp8xONTDisableChannel.0 u <gpon_port>
ltp8xONTDisableActionEnable.0 u 1
```

Where:

- <hex_serial> – serial number in hex format;
- <gpon_port> – the real value of the port number.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTDisableONTSerial.0 x
"454C545824A80012" ltp8xONTDisableChannel.0 u 6
ltp8xONTDisableActionEnable.0 u 1
```

The command performs ONT ELTX24A80012 activation on channel 6.

1.1.10 ONT firmware updating via OMCI protocol

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTFirmwareUpdateViaOMCISerial.0 x <hex_serial>
ltp8xONTFirmwareUpdateViaOMCIFilename.0 s <firmware_name>
ltp8xONTFirmwareUpdateViaOMCIAction.0 u 1
```

Where:

- <hex_serial> – serial number in hex format;
- <firmware_name> – the file name of the ONT firmware saved on OLT.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTFirmwareUpdateViaOMCISerial.0 x
"454C545824A80012" ltp8xONTFirmwareUpdateViaOMCIFilename.0 s "ntp-rg-revc
3.24.3.41.fw.bin" ltp8xONTFirmwareUpdateViaOMCIAction.0 u 1
```

The command starts the ONTELTX24A80012 update with the firmware file 'ntp-rg-revc-3.24.3.41.fw.bin'.

1.2 Requests

1.2.1 Common ONT state

The parameters of ONT state can be requested by using *ltp8xONTStateTable*.

Command format:

snmpget -v2c -c <ro_community> <ipaddr> <parameter_oid>.1.8.<dec_serial>

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xONTStateState.1.8.69.76.84.88.36.168.0.18
ltp8xONTStateVersion.1.8.69.76.84.88.36.168.0.18
```

The command requests the status and firmware version for the ONT ELTX24A80012.

1.2.2 PPP session state

To obtain the session list for selected ONT as the list of client MAC addresses, use the following request:

Command format:

**snmpwalk -v2c -c <ro_community> <ipaddr>
ltp8xOLTPPoESessionsClientMac.1.<gpon_port>.<ont_id>**

Where:

- <gpon_port> – port number increased by 1.

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xOLTPPoESessionsClientMac.1.7.0
```

The command requests the session list as the list of clients' MAC addresses for ONT 6/0.

To request information about specific PPPoE session, specify GPON port, ONT ID and client MAC address.

Command format:

**snmpget -v2c -c <ro_community> <ipaddr>
ltp8xOLTPPoESessionsPort.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPoESessionsSessionID.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPoESessionsDuration.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPoESessionsUnblock.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPoESessionsSerial.1.<gpon_port>.<ont_id>.6.<dec_client_mac>**

Where:

- <gpion_port> – port number increased by 1;
- <dec_client_mac> – client MAC address in decimal notation.

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xOLTPPPoESessionsPort.1.6.0.6.152.222.208.0.205.252
ltp8xOLTPPPoESessionsSessionID.1.6.0.6.152.222.208.0.205.252
ltp8xOLTPPPoESessionsDuration.1.6.0.6.152.222.208.0.205.252
ltp8xOLTPPPoESessionsUnblock.1.6.0.6.152.222.208.0.205.252
ltp8xOLTPPPoESessionsSerial.1.6.0.6.152.222.208.0.205.252
```

The command requests PPP session parameters with client MAC address 98:de:d0:00:cd:fc для ONT 6/0.

1.2.3 MAC table

Ltp8xONTAddressTable is used. To obtain the record list of the selected ONT, use the following request:

Command format:

**snmpwalk -v2c -c <ro_community> <ipaddr>
ltp8xONTAddressEntryID.1.8.<dec_serial>**

Example:

```
snmpwalk -v2c -c public 192.168.0.1
ltp8xONTAddressEntryID.1.8.69.76.84.88.36.168.0.18
```

The command requests MAC table record list of ONT ELTX24A80012.

To request MAC address table, specify ONT serial number and entry ID in the address table of the current ONT.

Command format:

**snmpget -v2c -c <ro_community> <ipaddr>
<parameter_oid>.1.8.<dec_serial>.<entry_id>**

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xONTAddressMacAddress.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTAddressCVID.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTAddressSVID.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTAddressUVID.1.8.69.76.84.88.36.168.0.18.1
```

The command requests MAC address, CVID, SVID, UVID for the first record in the MAC address table of ONT ELTX24A80012.

1.2.4 IGMP group table

ltp8xONTMulticastStatsTable is used. To obtain the record list of the selected ONT, use the following request:

Command format:

```
snmpwalk -v2c -c <ro_community> <ipaddr>
ltp8xONTMulticastStatsRecordID.1.8.<dec_serial>
```

Example:

```
snmpwalk -v2c -c public 192.168.0.1
ltp8xONTMulticastStatsRecordID.1.8.69.76.84.88.36.168.0.18
```

The command requests the record list of the IGMP group table for ONT ELTX24A80012.

To request the records of the IGMP group table, specify ONT serial number and entry ID in the IGMP-group table of the current ONT.

Command format:

```
snmpget -v2c -c <ro_community> <ipaddr>
<parameter_oid>.1.8.<dec_serial>.<entry_id>
```

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xONTMulticastStatsMulticastAddress.1.8.69.76.84.88.36.168.0.18.153
ltp8xONTMulticastStatsStop.1.8.69.76.84.88.36.168.0.18.153
ltp8xONTMulticastStatsStart.1.8.69.76.84.88.36.168.0.18.153
```

The command requests the IP address of the group, the broadcasting start and stop time for the 153rd entry in the ONT ELTX24A80012 IGMP group table.

1.2.5 ONT connection log

Command format:

```
snmpget -v2c -c <ro_community> <ipaddr>
ltp8xONTConnectionLogText.1.8.<dec_serial>
```

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xONTConnectionLogText.1.8.69.76.84.88.36.168.0.18
```

The command requests the connection log for ONT ELTX24A80012.

1.2.6 ONT timers

To obtain information about counters, use *Itp8xONTStatistics* table.

1.2.6.1 Counters for Cross-connect

Matches between counters and OIDs are given in the table below.

Table 1 – Matches between ONT and OID counters

Counter	OID	Description
CrossConnect in the downstream direction	Itp8xONTCrossConnectDSCounterName	CrossConnect counter name
	Itp8xONTCrossConnectDSCounterValue	CrossConnect counter value
CrossConnect in the upstream direction	Itp8xONTCrossConnectUSCounterName	CrossConnect counter name
	Itp8xONTCrossConnectUSCounterValue	CrossConnect counter value
GEM in the downstream direction	Itp8xONTGEMPortPerformMonitoringDSCounterName	GEM counter name
	Itp8xONTGEMPortPerformMonitoringDSCounterValue	GEM counter value
GEM in the upstream direction	Itp8xONTGEMPortPerformMonitoringUSCounterName	GEM counter name
	Itp8xONTGEMPortPerformMonitoringUSCounterValue	GEM counter value
GAL	Itp8xONTGalEthPerformMonitoringHistDataCounterName	GAL counter name
	Itp8xONTGalEthPerformMonitoringHistDataCounterValue	GAL counter value
FEC	Itp8xONTFecPerformMonitoringHistDataCounterName	FEC counter name
	Itp8xONTFecPerformMonitoringHistDataCounterValue	FEC counter value

Counter	OID	Description
Service utilization in the last 30 seconds	ltp8xONTServicesUtilizationLastUpstream	Upstream counter
	ltp8xONTServicesUtilizationLastDownstream	Downstream counter
Service utilization in the last 5 minutes	ltp8xONTServicesUtilizationAverageUpstream	Upstream counter
	ltp8xONTServicesUtilizationAverageDownstream	Downstream counter

Command format:

```
snmpwalk -v2c -c <ro_community> <ipaddr>
<parameter_oid>.1.8.<dec_serial>.<cross_connect_id>
```

Example:

```
snmpwalk -v2c -c public 192.168.0.1
ltp8xONTCrossConnectDSCounterName.1.8.69.76.84.88.36.168.0.18.1
snmpwalk -v2c -c public 192.168.0.1
ltp8xONTCrossConnectDSCounterValue.1.8.69.76.84.88.36.168.0.18.1
```

The command requests the name list of Cross-Connect counters for the downstream direction and their values for the first service of ONT ELTX24A80012.

1.2.6.2 ETH ports state

To obtain information about ports, use *ltp8xONTUNIPortsStateTable*.

Command format:

```
snmpget -v2c -c <ro_community> <ipaddr>
ltp8xONTUNIPortsStateAvailable.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStateLinkUp.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStateSpeed.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStateDuplex.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStatePoEEEnabled.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStatePoEPowerDetectionStatus.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStatePoEPowerClassificationStatus.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStatePoEPSEClassControl.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStatePoEPSEPowerPriority.1.8.<dec_serial>.<eth_port_id>
ltp8xONTUNIPortsStatePoECurrentPowerConsumption.1.8.<dec_serial>.<eth_port_id>
```

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xONTUNIPortsStateAvailable.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStateLinkUp.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStateSpeed.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStateDuplex.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStatePoEEEnabled.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStatePoEPowerDetectionStatus.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStatePoEPowerClassificationStatus.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStatePoEPSEClassControl.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStatePoEPSEPowerPriority.1.8.69.76.84.88.36.168.0.18.1
ltp8xONTUNIPortsStatePoECurrentPowerConsumption.1.8.69.76.84.88.36.168.0.18.1
```

The command requests the status of the 1st ETH port for the ONT ELTX24A80012.

1.2.6.3 ETH port counters

Matches between counters and OIDs are given in the table below.

Table 2 – Matches between ETH port and OID counters

Counter	OID	Description
ETH extended in the downstream direction	Itp8xONTEthFrameExtendedPerformMonitoringDSCo unterName	ETH extended counter name
	Itp8xONTEthFrameExtendedPerformMonitoringDSCo unterValue	ETH extended counter value
ETH extended in upstream direction	Itp8xONTEthFrameExtendedPerformMonitoringUSCo unterName	ETH extended counter name
	Itp8xONTEthFrameExtendedPerformMonitoringUSCo unterValue	ETH extended counter value
ETH	Itp8xONTEthPerformMonitoringHistDataCounterNa me	ETH counter name
	Itp8xONTEthPerformMonitoringHistDataCounterValu e	ETH counter value

Command format:

```
snmpwalk -v2c -c <ro_community> <ipaddr>
<parameter_oid>.1.8.<dec_serial>.<eth_port_id>
```

Example:

```
snmpwalk -v2c -c public 192.168.0.1
Itp8xONTEthFrameExtendedPerformMonitoringDSCounterName.1.8.69.76.84.88.36.168.0.18.1
snmpwalk -v2c -c public 192.168.0.1
Itp8xONTEthFrameExtendedPerformMonitoringDSCounterValue.1.8.69.76.84.88.36.168.0.18.1
```

The command requests the name list of ETH extended counters for the downstream direction and their values for the first ETH port of ONT ELTX24A80012.

1.2.6.4 Downstream BER counters

To obtain information about counters, use *ltp8xONTDownstreamBerTable*.

Command format:

snmpwalk -v2c -c <ro_community> <ipaddr> <parameter_oid>.1.<gpon_port>.8.<dec_serial>

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xONTDownstreamBerErrors.1.1.8.69.76.84.88.36.168.0.18
snmpwalk -v2c -c public 192.168.0.1 ltp8xONTDownstreamBerIntervals.
1.1.8.69.76.84.88.36.168.0.18
```

The command queries the BER Errors and BER Intervals counters for the ONT ELTX24A80012 at the zero GPON port.

To display the downstream BER counts for all connected ONTs, use the same command without specifying '.1.8.<dec_serial>'. In the example below, the command requests the BER Errors counters for all connected ONTs.

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xONTDownstreamBerErrors
```

1.2.6.5 Service utilization counters

To disable use the *ltp8xONTServicesUtilizationSettingsRowStatus* table

Command format:

snmpset -v2c -c <rw_community> <ipaddr> <parameter_oid>.1.8.<dec_serial>.<serviceID> i 4

Where:

<serviceID> – service number +1.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTServicesUtilizationSettingsRowStatus.
1.8.69.76.84.88.92.9.8.120.1 i 4
```

The command enables the utilization-enable parameter for service 0, ONT 454C54585C090878

1.2.6.6 Request metrics for service-utilization counters

To get the values OIDs used:

ltp8xONTServicesUtilizationLastUpstream – upstream counter for the last 30 seconds.

ltp8xONTServicesUtilizationLastDownstream – downstream counter for the last 30 seconds.

ltp8xONTServicesUtilizationAverageUpstream – upstream counter for the last 5 minutes.

ltp8xONTServicesUtilizationAverageDownstream – downstream counter for the last 5 minutes.

Command format:

snmpwalk -v2c -c <rw_community> <ipaddr> <parameter_oid>.1.8.<dec_serial>.<serviceID>

Where:

<serviceID> — service number +1.

Example:

```
snmpwalk -v2c -c private 192.168.0.1 ltp8xONTServicesUtilizationLastUpstream.  
1.8.69.76.84.88.92.9.8.120.2  
snmpwalk -v2c -c private 192.168.0.1 ltp8xONTServicesUtilizationLastDownstream.  
1.8.69.76.84.88.92.9.8.120.2  
snmpwalk -v2c -c private 192.168.0.1 ltp8xONTServicesUtilizationAverageUpstream.  
1.8.69.76.84.88.92.9.8.120.2  
snmpwalk -v2c -c private 192.168.0.1 ltp8xONTServicesUtilizationAverageDownstream.  
1.8.69.76.84.88.92.9.8.120.2
```

Commands request the counters for each parameter for service 1.

1.2.6.7 Service-utilization counters disabling

Command format:

snmpset -v2c -c <rw_community> <ipaddr> <parameter_oid>.1.8.<dec_serial>.<serviceID> i 6

Where:

<serviceID> — service number +1.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTServicesUtilizationSettingsRowStatus.  
1.8.69.76.84.88.92.9.8.120.1 i 6
```

The command disables the utilization-enable parameter for service 0, ONT 454C54585C090878.

1.2.7 Counter reset on ONT

Command format:

**snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTResetCountersAction.1.8.<dec_serial> u 1**

Example:

```
snmpset -v2c -c private 192.168.0.1  
ltp8xONTResetCountersAction.1.8.69.76.84.88.36.168.0.18 u 1
```

The command resets ONT ELTX24A80012 counters.

1.2.8 GPON port counter reset

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xPONChannelResetCounters.1.<gpon_port> u 1
```

Where:

- <gpon_port> – port number increased by 1.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xPONChannelResetCounters.1.7 u 1
```

The command resets the counters of GPON port 6.

2 OLT configuration

Connection to LTP is possible either with a console cable or with an Ethernet cable to the GE port.

2.1 Applying and confirming configuration

A configuration commit occurs automatically when configuration changes are made.

2.1.1 Save configuration into non-volatile memory

Command format:

snmpset -v2c -c <rw_community> -t 20 <ipaddr> ltp8xSaveConfig.0 u 1

Example:

```
snmpset -v2c -c private -t 20 192.168.0.1 ltp8xSaveConfig.0 u 1
```

2.1.2 Reread configuration from non-volatile memory

Command format:

snmpset -v2c -c <rw_community> -t 20 <ipaddr> ltp8xRereadConfig.0 u 1

Example:

```
snmpset -v2c -c private -t 20 192.168.0.1 ltp8xRereadConfig.0 u 1
```

2.2 VLAN Configuration

VLAN configuration is done using the *ltp8xSwitchVLANTable*.

2.2.1 Adding a VLAN

Command format:

snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchVLANRowStatus.1.<vlan_id> i 4

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchVLANRowStatus.1.156 i 4
```

The command creates VLAN 156.

2.2.2 Editing a VLAN

VLAN port membership is specified by two bitmasks each of them has value 1 in the N-th bit (big-endian). It means including a port with Index N into this variety. Port index distribution can be checked in *ltp8xSwitchPortsTable*. Convert bit masks into hex format to substitute them in **snmpset** commands.

There are two sets: *TaggedPorts* and *UntaggedPorts*.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchVLANNName.1.<vlan_id> s
"vlan_name" ltp8xSwitchVLANTaggedPorts.1.<vlan_id> x "<ports_mask>"
ltp8xSwitchVLANUntaggedPorts.1.<vlan_id> x "<ports_mask>"
```

ltp8xSwitchVLANIGMPSnoopingEnabled.1.<vlan_id> i 1/2
 ltp8xSwitchVLANMLDSnoopingEnabled.1.<vlan_id> i 1/2
 ltp8xSwitchVLANIGMPQueryInterval.1.<vlan_id> u <value>
 ltp8xSwitchVLANMLDQueryInterval.1.<vlan_id> u <value>
 ltp8xSwitchVLANIGMPMrouterPorts.1.<vlan_id> x <ports_mask>
 ltp8xSwitchVLANMLDMrouterPorts.1.<vlan_id> x <ports_mask>
 ltp8xSwitchVLANIsolationEnabled.1.<vlan_id> i 1/2
 ltp8xSwitchVLANIsolationGroup.1.<vlan_id>.<group_id> u <port_id>

Where:

- <ports_mask> – bitmask values;
- <group_id> – insulation group number value increased by 1;
- <port_id> – port index value according to *ltp8xSwitchPortsTable*.

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xSwitchVLANNName.1.156 s "edited_by_snmp"
ltp8xSwitchVLANTaggedPorts.1.156 x "40000000"
ltp8xSwitchVLANUntaggedPorts.1.156 x "20000000"
ltp8xSwitchVLANIGMPSnoopingEnabled.1.156 i 1
ltp8xSwitchVLANMLDSnoopingEnabled.1.156 i 1
ltp8xSwitchVLANIGMPQueryInterval.1.156 u 300
ltp8xSwitchVLANMLDQueryInterval.1.156 u 400
ltp8xSwitchVLANIGMPMrouterPorts.1.156 x "FF000000"
ltp8xSwitchVLANMLDMrouterPorts.1.156 x "FF000000"
ltp8xSwitchVLANIsolationEnabled.1.156 i 1
ltp8xSwitchVLANIsolationGroup.1.156.2 u 3
```

The command sets the name 'edited_by_snmp' for VLAN 156, adds pon-port 1 tagged, pon-port 2 untagged, enables IGMP and MLD snooping, sets IGMPQueryInterval=300 and MLDQueryInterval=400, removes IGMP and MLD snooping mrouter 10G-front-port 0-1 interfaces, enables isolation and assigns vlan to isolation group 2.

2.2.3 Deleting a VLAN

Command format:

snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchVLANRowStatus.1.<vlan_id> i 6

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchVLANRowStatus.1.156 i 6
```

The command deletes VLAN 156 from the configuration.

2.2.4 Requesting the list of VLANs and configuring a specific VLAN

To request the list of VLANs, use the following request.

Command format:

snmpwalk -v2c -c <ro_community> <ipaddr> ltp8xSwitchVLANNName.1

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xSwitchVLANNName.1
```

The command lists VLANs.

To configure a specific VLAN, use the following request.

Command format:

**snmpget -v2c -c <ro_community> <ipaddr> ltp8xSwitchVLANNName.1.<vlan_id>
ltp8xSwitchVLANTaggedPorts.1.<vlan_id> ltp8xSwitchVLANUntaggedPorts.1.<vlan_id>
ltp8xSwitchVLANIGMP SnoopingEnabled.1.<vlan_id>
ltp8xSwitchVLANIGMP SnoopingQuerierEnabled.1.<vlan_id>
ltp8xSwitchVLANIGMPQueryInterval.1.<vlan_id>
ltp8xSwitchVLANMLDSnoopingEnabled.1.<vlan_id>
ltp8xSwitchVLANMLDSnoopingQuerierEnabled.1.<vlan_id>
ltp8xSwitchVLANMLDQueryInterval.1.<vlan_id>
ltp8xSwitchVLANIGMP RouterPorts.1.<vlan_id>
ltp8xSwitchVLANMLD RouterPorts.1.<vlan_id>
ltp8xSwitchVLANIsolationEnabled.1.<vlan_id>
ltp8xSwitchVLANIsolationGroup.1.<vlan_id>.<group_id>**

Example:

```
snmpget -v2c -c public 192.168.0.1 ltp8xSwitchVLANNName.1.156  
ltp8xSwitchVLANTaggedPorts.1.156 ltp8xSwitchVLANUntaggedPorts.1.156  
ltp8xSwitchVLANIGMP SnoopingEnabled.1.156  
ltp8xSwitchVLANIGMP SnoopingQuerierEnabled.1.156  
ltp8xSwitchVLANIGMPQueryInterval.1.156  
ltp8xSwitchVLANMLDSnoopingEnabled.1.156  
ltp8xSwitchVLANMLDSnoopingQuerierEnabled.1.156  
ltp8xSwitchVLANMLDQueryInterval.1.156 ltp8xSwitchVLANIGMP RouterPorts.1.156  
ltp8xSwitchVLANMLD RouterPorts.1.156 ltp8xSwitchVLANIsolationEnabled.1.156  
ltp8xSwitchVLANIsolationGroup.1.156.2
```

The command displays the configuration of a specific VLAN.

2.3 Terminal VLAN Configuration

2.3.1 Adding Terminal VLAN

Use *ltp8xOLTTerminalVLANSNamesTable* to add Terminal VLAN.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xOLTTerminalVLANSNamesRowStatus.<t_vlan_id> i 4
ltp8xOLTTerminalVLANSNamesName.<t_vlan_id> s "<t_vlan_name>"
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xOLTTerminalVLANSNamesRowStatus.1 i 4
ltp8xOLTTerminalVLANSNamesName.1 s "created_by_snmp"
```

The command creates Terminal VLAN with index 1 and name 'created_by_snmp'.

2.3.2 Editing Terminal VLAN

Use *ltp8xOLTTerminalVLANSTable* to edit Terminal VLAN parameters.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xOLTTerminalVLANSVID.1.<t_vlan_id> u <vlan_id>
ltp8xOLTTerminalVLANSCos.1.<t_vlan_id> i <cos>
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xOLTTerminalVLANSVID.1.1 u 80
ltp8xOLTTerminalVLANSCos.1.1 i 255
```

The command sets the Terminal VLAN with index 1 to vlan_id = 80, cos = unused.

2.3.3 Deleting Terminal VLAN

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xOLTTerminalVLANSNamesRowStatus.<t_vlan_id> i 6
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xOLTTerminalVLANSNamesRowStatus.1 i 6
```

The command deletes Terminal VLAN with index 1 from configuration.

2.3.4 Requesting the list of Terminal VLANs and configuring a specific Terminal VLAN

To get the list of Terminal VLANs, use the following request.

Command format:

```
snmpwalk -v2c -c <ro_community> <ipaddr>  
ltp8xOLTTerminalVLANsNamesName
```

Example:

```
snmpwalk -v2c -c public 192.168.0.1  
ltp8xOLTTerminalVLANsNamesName
```

The command lists Terminal VLANs.

To obtain configuration of the specific VLAN, use the following request.

Command format:

```
snmpget -v2c -c <ro_community> <ipaddr>  
ltp8xOLTTerminalVLANsName.1.<t_vlan_id>  
ltp8xOLTTerminalVLANsVID.1.<t_vlan_id>  
ltp8xOLTTerminalVLANsCOS.1.<t_vlan_id>
```

Example:

```
snmpget -v2c -c public 192.168.0.1  
ltp8xOLTTerminalVLANsName.1.1  
ltp8xOLTTerminalVLANsVID.1.1  
ltp8xOLTTerminalVLANsCOS.1.1
```

The command displays the configuration of a specific Terminal VLAN.

2.4 IGMP/MLD Configuration

2.4.1 Global settings for enabling IGMP/MLD Snooping

To configure IGMP/MLD, use *ltp8xSwitchIGMPSnoopingTable*. OIDs for configuring global parameters are listed in the table below.

Table 3 – OID compliance for global settings

Parameter	OID	Description
IGMP Snooping	ltp8xSwitchIGMPSnoopingEnabled	Possible values: 1 – Enable 2 – Disable
MLD Snooping	ltp8xSwitchMLDSnoopingEnabled	

Command format:

snmpset -v2c -c <rw_community> <ipaddr> <parameter_oid>.1 i <value>

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchIGMPSnoopingEnabled.1 i 1
```

The command enables IGMP Snooping.

2.4.2 IGMP Snooping and VLAN Querier configuration

This setting is carried out similarly to the [Editing a VLAN](#) section.

2.5 OLT, ONT profiles configuration

2.5.1 Address-table

Operation with address-table profiles is performed using *ltp8xOLTAddressTableProfilesTable* and *ltp8xOLTAddressTableProfileSVLANTable*. Profiles and each S-VLAN for the profile are configured separately.

2.5.1.1 Addition

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xOLTAddressTableProfilesRowStatus.<profile_index> i 4
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xOLTAddressTableProfileSVLANRowStatus.<profile_index>.<vlan_id> i 4
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xOLTAddressTableProfilesRowStatus.2 i 4
snmpset -v2c -c private 192.168.0.1 ltp8xOLTAddressTableProfileSVLANRowStatus.2.1234 i 4
```

The command adds an address-table profile with index 2. Sets this profile to s-vlan 1234.

2.5.1.2 Configuration

To configure profile and s-vlan parameters use *ltp8xOLTAddressTableProfilesTable* and *ltp8xOLTAddressTableProfileSVLANTable*.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
<parameter_oid_ProfilesTable>.<profile_id> <par_type> <par_value>
<parameter_oid_ProfileSVLANTable>.<profile_id>.<vlan_id> <par_type> <par_value>
```

Where:

<parameter_oid_ProfilesTable> – names of specific parameters in the MIB from *ltp8xOLTAddressTableProfilesTable*;
 <parameter_oid_ProfileSVLANTable> – names of specific parameters in the MIB from *ltp8xOLTAddressTableProfileSVLANTable*;
 <profile_id> – profile index;
 <par_type> – parameter value type;
 <par_value> – parameter value.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xOLTAddressTableProfilesDescription.2 s
"edited_by_snmp"
```

The command sets the address-table profile with index 2 to 'edited_by_snmp'.

2.5.1.3 Deletion

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xOLTAddressTableProfilesRowStatus.<profile_index> i 6
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xOLTAddressTableProfileSVLANRowStatus.<profile_index>.<vlan_id> i 6
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xOLTAddressTableProfilesRowStatus.2 i 6
snmpset -v2c -c private 192.168.0.1 ltp8xOLTAddressTableProfileSVLANRowStatus.2.1234 i 6
```

The commands remove the address-table profile with index 2, and the S-VLAN 1234 binding to the address-table profile with index 2.

2.5.2 Cross-connect

For operation with cross-connect profile, use *ltp8xONTCrossConnectProfileTable*.

2.5.2.1 Addition

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTCrossConnectRowStatus.<profile_index> i 4
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTCrossConnectRowStatus.2 i 4
```

The command adds Cross-connect profile with index 2.

2.5.2.2 Editing

A feature of Cross-connect profiles is that if you specify a link to terminal-vlan as *vlan_id*, the value is passed from -100 (terminal-vlan-0) to -131 (terminal-vlan-31).

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
<parameter_oid_1>.<profile_id> <par1_type> <par1_value>
<parameter_oid_2>.<profile_id> <par2_type> <par2_value>
...
<parameter_oid_N>.<profile_id> <parN_type> <parN_value>
```

Where:

- <parameter_oid_N> – the names of specific MIB parameters;
- <profile_id> – profile index;
- <parN_type> – value type of a parameter;
- <parN_value> – parameter value.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTCrossConnectName.2 s
"edited_by_snmp" ltp8xONTCrossConnectModel.2 i 1
ltp8xONTCrossConnectBridgeGroup.2 u 5 ltp8xONTCrossConnectUVID.2 i -101
```

For Cross-connect with index 2, the command sets name 'edited_by_snmp', bridge group = 5 and UVID linking on terminal-vlan-1.

2.5.2.3 Deletion

Command format:

snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTCrossConnectRowStatus.<profile_index> i 6

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTCrossConnectRowStatus.2 i 6
```

The command deletes Cross-connect profile with index 2.

2.5.2.4 Profile list request

Command format:

snmpwalk -v2c -c <ro_community> <ipaddr> ltp8xONTCrossConnectName

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xONTCrossConnectName
```

2.5.3 DBA

For operation with DBA profiles, use *ltp8xONTAllocProfileTable*.

2.5.3.1 Addition

Command format:

snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTAllocRowStatus.<profile_index> i 4

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTAllocRowStatus.3 i 4
```

The command adds DBA profile with index 3.

2.5.3.2 Editing

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
<parameter_oid_1>.<profile_id> <par1_type> <par1_value>
<parameter_oid_2>.<profile_id> <par2_type> <par2_value>
.....
<parameter_oid_N>.<profile_id> <parN_type> <parN_value>
```

Where:

- <parameter_oid_N> – the names of specific MIB parameters;
- <profile_id> – profile index;
- <parN_type> – value type of a parameter;
- <parN_value> – parameter value.

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xONTAllocName.3 s "edited_by_snmp"
ltp8xONTAllocServiceClass.3 i 3
ltp8xONTAllocFixedBandwidth.3 u 269248
```

The command sets the name 'edited_by_snmp', service class = cbr and fixed bandwidth 3 for DBA profile with index 3.

2.5.3.3 Deletion

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTAllocRowStatus.<profile_index> i 6
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTAllocRowStatus.3 i 6
```

The command deletes DBA profile with index 3.

2.5.3.4 Profile list request

Command format:

```
snmpwalk -v2c -c <ro_community> <ipaddr> ltp8xONTAllocName
```

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xONTAllocName
```

2.5.4 Ports

For operation with Ports profile, use the following tables:

- **ltp8xONTPortsProfileTable** – general profile parameters;
- **ltp8xONTPortsProfileUNITable** – UNI ports;
- **ltp8xONTPortsProfileMCDynamicEntriesTable** – IGMP multicast dynamic entries;
- **ltp8xONTPortsProfileMLDDynamicEntriesTable** – MLD multicast dynamic entries.

2.5.4.1 Addition

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTPortsRowStatus.<profile_index> i 4
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTPortsRowStatus.4 i 4
Команда добавляет профиль Ports с индексом 4.
```

2.5.4.2 Editing

General parameters:

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> <parameter_oid_1>.<profile_id>
<par1_type> <par1_value> <parameter_oid_2>.<profile_id> <par2_type>
<par2_value> ... <parameter_oid_N>.<profile_id>
<parN_type> <parN_value>
```

Where:

- <parameter_oid_N> – the names of specific MIB parameters;
- <profile_id> – profile index;
- <parN_type> – value type of a parameter;
- <parN_value> – parameter value.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTPortsName.4 s
"edited_by_snmp" ltp8xONTPortsMulticastIPVersion.4 i 1
ltp8xONTPortsMLDVersion.4 u 1 ltp8xONTPortsMLDQueryInterval.4 u 120
```

The command sets name 'edited_by_snmp', IPv6 usage, MLDv1 version and MLD query interval 4 for Ports profile with index 4.

The parameters of UNI ports:

In addition to profile index, specify port index (0–3).

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTPortsUNIBridgeGroup.4.0 i
100 ltp8xONTPortsUNIMulticastEnabled.4.0 i 1
ltp8xONTPortsUNIMaxGroups.4.0 u 500
```

For Port profile with index 4 on port with index 0, the command sets parameters, bridge group = 100 and max groups = 500 , and enables multicast.

IGMP multicast dynamic entries:

In addition to profile index, specify dynamic entry index (0–19).

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTPortsMCVLANID.4.14 u 200
ltp8xONTPortsMCFirstGroupIP.4.14 a 224.0.0.0
ltp8xONTPortsMCLastGroupIP.4.14 a 239.255.255.255
```

The command sets the following values for the multicast dynamic entry parameter (with index 14) of the Ports profile (with index 4): vlan_id = 200, first group ip = 224.0.0.0, last group ip = 239.255.255.255.

MLD multicast dynamic entries:

In addition to profile index, specify dynamic entry index (0–19).

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTPortsMLDVLANID.4.12 u 30
ltp8xONTPortsMLDMCFirstGroupIP.4.12 x "FF010000000000000000000000000000FC"
ltp8xONTPortsMLDMCLastGroupIP.4.12 x "FF010000000000000000000000000000FD"
ltp8xONTPortsMLDMCPreviewLength.4.12 u 1024
```

The command sets the following values for the multicast dynamic entry parameter (with index 12) of the Ports profile (with index 4): vlan_id = 30, first group ip = FF01:0:0:0:0:0:FC, last group ip = FF01:0:0:0:0:0:FD and preview length = 1024.

2.5.4.3 Deletion

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTPortsRowStatus.<profile_index> i 6
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTPortsRowStatus.4 i 6
The command deletes Ports profile with index 4.
```

2.5.4.4 Profile list request

Command format:

snmpwalk -v2c -c <ro_community> <ipaddr> ltp8xONTPortsName

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xONTPortsName
```

2.6 PON channels

2.6.1 Enabling/disabling PON channels

Command format:

**snmpset -v2c -c <rw_community> <ipaddr>
ltp8xPONChannelEnabled.1.<gpon_port> i <value>**

Where:

- <gpon_port> – port number increased by 1;
- <value> – possible values: 1 – Enable; 2 – Disable.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xPONChannelEnabled.1.1 i 2
```

The command disables gpon-port 0.

2.6.2 Reconfiguration

Command format:

**snmpset -v2c -c <rw_community> <ipaddr>
ltp8xPONChannelReconfigure.1.<gpon_port> u 1**

Where:

- <gpon_port> – port number increased by 1.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xPONChannelReconfigure.1.1 u 1
```

The command reconfigures gpon-port 0.

2.6.3 Unknown multicast forwarding enabling

This command allows you to pass unknown multicast traffic on the gpon port.

Command format:

snmpset -v2c -c <rw_community> <ipaddr> ltp8xPONChannelUnknownMulticastForwardEnabled.1.<GPON-port-id>

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xPONChannelUnknownMulticastForwardEnabled.1.1 i 1
```

The command enables unknown multicast forwarding on GPON port 1.

2.6.4 Viewing counters

Viewing the counter of pon channel is performed by request of the corresponding switch PON port.

Correspondence of pon-channels to port indexes in switch are listed in the *ltp8xSwitchPortsName* table.

2.6.4.1 Ethernet counters

Request is performed by using *ltp8xSwitchPortCountersTable*.

Command format:

snmpget -v2c -c <ro_community> <ipaddr> <counter_oid>.1.<port_index>

Example:

```
snmpget -v2c -c public 192.168.0.1 ltp8xSwitchPortGoodOctetsRcv.1.16
ltp8xSwitchPortGoodPktsRcv.1.16
```

The command requests the number of received octets and packets for the 3rd pon channel.

2.6.4.2 Interface utilization

Request is performed by using *ltp8xSwitchPortsUtilization*.

Command format:

snmpget -v2c -c <ro_community> <ipaddr> <utilization_oid>.1.<port_index>

Example:

```
snmpget -v2c -c public 192.168.0.1 ltp8xPortsUtilizationLastKbitsSent.1.20
ltp8xPortsUtilizationLastKbitsRecv.1.20
ltp8xPortsUtilizationLastFramesSent.1.20
ltp8xPortsUtilizationLastFramesRecv.1.20
ltp8xPortsUtilizationAverageKbitsSent.1.20
ltp8xPortsUtilizationAverageKbitsRecv.1.20
ltp8xPortsUtilizationAverageFramesSent.1.20
ltp8xPortsUtilizationAverageFramesRecv.1.20
```

The command requests utilization parameters for the 7th pon channel.

2.7 Switch interfaces configuration

This section describes PVID assigning and bridging configuration.

2.7.1 PVID assigning

PVID configuration is done using the *ltp8xSwitchPortConfigPVID* table.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xSwitchPortConfigPVID.1.<port_index> u <vlan_id>
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchPortConfigPVID.1.2 u 156
```

The command will set the value pvid=156 for front-port 1.

2.7.2 Bridging configuration

Bridging ports configuration performed using the *ltp8xSwitchPortConfigBridging* table. Configuration is performed using two bitmasks, each of them has value 1 in the N-th bit (big-endian). It means including a port with ifIndex = N into this variety. Port index distribution can be checked in *ltp8xSwitchPortsTable*. Convert bit masks into hex format to substitute them in **snmpset** commands.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xSwitchPortConfigBridging.1.<port_index> x <ports_mask>
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchPortConfigBridging.1.6 x 0033F000
```

The command will set bridging on pon-port 0-7 for front-port 5 interface.

2.7.3 Port Channel configuration

Port-Channel configuration is performed using *ltp8xSwitchPortGroupTable* and *ltp8xSwitchPortConfigGroup*.

2.7.3.1 Addition

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchPortConfigGroup.1.<port_channel_index> i 4
```

Where:

- <port_channel_index> – Channel Group index.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchPortGroupRowStatus.1.3 i 4
```

The command adds Channel Group with index 3.

2.7.3.2 Editing

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchPortConfigGroup.1.<interface_id> u
<port_channel_index>
```

Where:

- <interface_id> – interface index, in accordance with *ltp8xSwitchPortsTable*.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchPortConfigGroup.1.8 u 3
```

The command includes Front-Port 7 in Channel Group with index 3.

2.7.3.3 Deletion

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchPortConfigGroup.1.<port_channel_index> i 6
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchPortGroupRowStatus.1.3 i 6
```

The command deletes Channel Group with index 3.

2.7.4 Multicast loopback configuration

Multicast loopback configuration is performed using *ltp8xSwitchVLANTable* and *ltp8xSwitchPortConfigTable*. Port index distribution can be checked in *ltp8xSwitchPortsTable*.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchVLANMulticastLoopbackEnabled.1.<vlan_id>
snmpset -v2c -c <rw_community> <ipaddr> ltp8xSwitchPortConfigMulticastLoopbackPonEnabled.
1.<interface_pon_port_id>
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchVLANMulticastLoopbackEnabled.1.205
snmpset -v2c -c private 192.168.0.1 ltp8xSwitchPortConfigMulticastLoopbackPonEnabled.1.15
```

The commands activate multicast loopback for VLAN id 205 and pon-port 2.

2.8 IP Source Guard configuration

IP Source Guard configuration is performed using *ltp8xIPSourceGuard* table.

2.8.1 Operating mode enabling and configuration

Enabling and configuring the IP Source Guard operating mode is done using the *ltp8xIPSourceGuardConfigTable*.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xIPSourceGuardEnabled.1 i
1/2 ltp8xIPSourceGuardMode.1 u 0/1 ltp8xIPSourceGuardDatabaseEnabled.1 i
1/2 ltp8xIPSourceGuardDatabaseUpdateFreq.1 u <value>
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xIPSourceGuardEnabled.1 i 1
ltp8xIPSourceGuardMode.1 u 0 ltp8xIPSourceGuardDatabaseEnabled.1 i 1
ltp8xIPSourceGuardDatabaseUpdateFreq.1 u 1020
```

The command activates IP Source Guard, sets the mode to static, activates IP Source Guard Database and sets the retention period to 1020 seconds.

2.8.2 IP Source Guard Bind configuration

IP Source Guard Bind configuration is performed using *ltp8xIPSourceGuardBindTable*.

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xIPSourceGuardBindRowStatus.1.1.2.3.4 i <value>
ltp8xIPSourceGuardBindMAC.1.1.2.3.4 s "<MAC-addr>"
ltp8xIPSourceGuardBindONTChannel.1.1.2.3.4 u <gpon-port>
ltp8xIPSourceGuardBindONTID.1.1.2.3.4 u <ONT-id>
ltp8xIPSourceGuardBindService.1.1.2.3.4 u <ONT-service-id>
```

Example:

```
snmpset -v2c -c private 192.168.0.1
ltp8xIPSourceGuardBindRowStatus.1.1.2.3.4 i 4
ltp8xIPSourceGuardBindMAC.1.1.2.3.4 s "33:33:33:22:22:22"
ltp8xIPSourceGuardBindONTChannel.1.1.2.3.4 u 1 ltp8xIPSourceGuardBindONTID.1.1.2.3.4 u 1
ltp8xIPSourceGuardBindService.1.1.2.3.4 u 2
```

The command creates a static binding of the source IP address 1.2.3.4 to the MAC address 33:33:33:22:22:22 and service 2 on the ONT.

2.8.3 IP Source Guard Ignored Vlan configuration

IP Source Guard Ignored Vlan configuration is performed using *ltp8xIPSourceGuardIgnoredVlanTable*.

Command format:

snmpset -v2c -c <rw_community> <ipaddr> ltp8xIPSourceGuardIgnoredVlanRowStatus.1.<vlan_id> i <value>

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xIPSourceGuardIgnoredVlanRowStatus.1.222 i 4
```

The command will disable IPSG in the specified VLAN 222.

3 Operations for uploading/downloading OLT firmware (TFTP/HTTP)

3.1 OLT firmware download

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> cmdFileOperationBinaryCfg.0 s
"<server_ip> <file_path> <download_protocol>"
```

Where:

- <server_ip> – IP address of the tftp/http server with firmware file;
- <file_path> – full path to the file on the server;
- <download_protocol> – takes the values of download/httpdownload for downloading by tftp/http, respectively.

Example:

```
snmpset -v2c -c private -t 20 -r 0 192.168.0.1
cmdFileOperationBinaryCfg.0 s "192.168.16.55:8080 station_images/ltp-8x
revc-3.32.0.1260.fw.bin httpdownload"
```

The command downloads the firmware file station_images/ltp-8x-revc-3.32.0.1260.fw.bin from the http server 192.168.0.55, a device reboot is required to apply the firmware.

3.2 Current LTP firmware request

Command format:

```
snmpget -v2c -c <ro_community> <ipaddr> ltp8xFirmwareRevision.0
```

Example:

```
snmpget -v2c -c public 192.168.0.1 ltp8xFirmwareRevision.0
```

3.3 Reboot

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xRebootTimeout.0 u <value>
```

Where:

- <value> – value of the timeout before device reboot, in seconds.

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xRebootTimeout.0 u 0
```

The command immediately reboots the device.

3.4 ONT firmware

3.4.1 Firmware downloading

To download the ONT firmware, use the *ltp8xONTFirmwaresDownload* group of parameters.

Parameter	Description
ltp8xONTFirmwaresDownloadPath	The name of the ONT FW file
ltp8xONTFirmwaresDownloadIPAddress	IP address of the server storing firmware file
ltp8xONTFirmwaresDownloadProtocol	The protocol for access to http/tftp file
ltp8xONTFirmwaresDownloadPort	A server port with firmware file
ltp8xONTFirmwaresDownloadAction	Initiate update process

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr> ltp8xONTFirmwaresDownloadPath.0 s "<file_name>"  
ltp8xONTFirmwaresDownloadIPAddress.0 a <server_ip>  
ltp8xONTFirmwaresDownloadProtocol.0 i <download_protocol>  
ltp8xONTFirmwaresDownloadPort.0 u <server_port>  
ltp8xONTFirmwaresDownloadAction.0 u 1
```

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTFirmwaresDownloadPath.0 s  
"ntp-rg-revb-3.24.3.87.fw.bin" ltp8xONTFirmwaresDownloadIPAddress.0 a  
192.168.0.55 ltp8xONTFirmwaresDownloadProtocol.0 i 2  
ltp8xONTFirmwaresDownloadPort.0 u 8080 ltp8xONTFirmwaresDownloadAction.0 u 1
```

The command downloads the firmware file ntp-rg-revb-3.24.3.87.fw.bin from port 8080 of HTTP server 192.168.0.55.

3.4.2 Requesting a list of downloaded firmware files

Command format:

```
snmpwalk -v2c -c <ro_community> <ipaddr> ltp8xONTFirmwaresFileName
```

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xONTFirmwaresFileName
```

3.4.3 Deleting uploaded firmware

Command format:

```
snmpset -v2c -c <rw_community> <ipaddr>
ltp8xONTFirmwaresFilesDelete.<file_id> u 1
```

Where:

- <file_id> – ONT firmware file ID in the list (see section 3.3.2).

Example:

```
snmpset -v2c -c private 192.168.0.1 ltp8xONTFirmwaresFilesDelete.2 u 1
```

The command deletes firmware file with index 2.

3.5 Configuration uploading/downloading

3.5.1 Backup configuration uploading

Command format:

Via TFTP:

```
snmpset -v2c -c <rw_community> <ipaddr> cmdFileOperationPrivateCfg.0 s
"<tftp_server_ip> <tftp_path> upload"
```

Via HTTP:

```
snmpset -v2c -c <rw_community> <ipaddr> cmdFileOperationPrivateCfg.0 s
"<http_sever_ip> <http_path> httpupload"
```

Where:

- <tftp_path>, <http_path> – full path for uploading file on the server.

Example:

```
snmpset -v2c -c private 192.168.0.1 cmdFileOperationPrivateCfg.0 s
"192.168.0.55 new_config.cfg upload"
```

The command uploads the configuration via TFTP to the server 192.168.0.55 in a file named new_config.cfg.

3.5.2 Backup configuration downloading

Command format:

Via TFTP:

```
snmpset -v2c -c <rw_community> <ipaddr> cmdFileOperationPrivateCfg.0 s
"<tftp_ip> <tftp_path> download"
```

Via HTTP:

```
snmpset -v2c -c <rw_community> <ipaddr> cmdFileOperationPrivateCfg.0 s
"<http_ip> <http_path> httpdownload"
```

Where:

- <tftp_path>, <http_path> – full path for downloading file from the server.

Example:

```
snmpset -v2c -c private 192.168.0.1 cmdFileOperationPrivateCfg.0 s
"192.168.0.55:8080 config/new_config.cfg httpdownload"
```

The command downloads configurations via TFTP from config/new_config.cfg. file locating on the server 192.168.0.55. After the download is finished, it is required to apply the configuration using the following commands.

Command format:

Via TFTP:

```
snmpset -v2c -c <rw_community> <ipaddr> cmdFileOperationPrivateCfg.0 s
"<tftp_ip> <tftp_path> apply"
```

Via HTTP:

```
snmpset -v2c -c <rw_community> <ipaddr> cmdFileOperationPrivateCfg.0 s
"<http_ip> <http_path> apply"
```

Where:

- <tftp_path>, <http_path> – full path for downloading file from the server.

Example:

```
snmpset -v2c -c private 192.168.0.1 cmdFileOperationPrivateCfg.0 s
"192.168.0.55:8080 config/new_config.cfg apply"
```

4 OLT monitoring

4.1 Active alarms

Getting the number of active alarms

Command format:

snmpget -v2c -c <ro_community> <ipaddr> omsActiveAlarms.0

Example:

```
snmpget -v2c -c public 192.168.0.1 omsActiveAlarms.0
```

Getting the active alarms in trap forms

Command format:

snmpset -v2c -c <rw_community> <ipaddr> omsActiveAlarms.0 u 1

Example:

```
snmpset -v2c -c private 192.168.0.1 omsActiveAlarms.0 u 1
```

The command sends request to display all the device active alarms by snmp-trap messages.

4.2 LTP general information

General information about LTP is collected in the *ltp8xSystem* and *ltp8xBoardStatus* groups.

Command format:

snmpget -v2c -c <ro_community> <ipaddr> <parameter_oid>.0

Example:

```
snmpget -v2c -c public 192.168.0.1 ltp8xSystemMacAddress.0
ltp8xFan1RPM.0 ltp8xRAMFree.0
```

The command displays the LTP MAC address and current Fan1 fan speed, and the amount of free memory in bytes.

4.3 Power supply

General information about LTP power modules is collected in the *ltp8xPowerSupplyTable*.

Command format:

snmpget -v2c -c <ro_community> <ipaddr> <parameter_oid>.<module_id>

Example:

```
snmpget -v2c -c public 192.168.0.1 ltp8xPowerSupplyModulePresent.1
ltp8xPowerSupplyModuleName.1 ltp8xPowerSupplyModuleType.1
ltp8xPowerSupplyModuleIntact.1
```

The command displays the presence of the power module with id=1, its name and type of input voltage.

4.4 Port and PON channel state

The *ifTable* is used to display port status.

Command format:

snmpget -v2c -c <ro_community> <ipaddr> ifOperStatus.<ifIndex>

Example:

```
snmpget -v2c -c public 192.168.0.1 ifOperStatus.11
```

The command displays the front-port 2 state.

To display the status of pon channels, use the *ltp8xPONChannelStateTable*.

Command format:

snmpget -v2c -c <ro_community> <ipaddr> <parameter_oid>.1.<pon_channel_id>

Example:

```
snmpget -v2c -c public 192.168.0.1 ltp8xPONChannelONTCount.1.4
ltp8xPONChannelSFPVendor.1.4
ltp8xPONChannelSFPPProductNumber.1.4 ltp8xPONChannelSFPRRevision.1.4
```

The command displays the number of ONTs and SFP data for channel 3.

4.5 MAC Table

To display switch MAC addresses, use the *ltp8xSwitchMacListTable*.

Switch MAC address table

Command format:

**snmpwalk -v2c -c <ro_community> <ipaddr>
ltp8xSwitchMacListMacAddressString.1**

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xSwitchMacListMacAddressString.1
```

The command displays the MAC address table in a list.

After that, if you know the parameters of a particular record, you can additionally request an interface and type for it.

Command format:

**snmpget -v2c -c <ro_community> <ipaddr>
ltp8xSwitchMacListInterface.1.<vlan_id>.<dec_macaddress>
ltp8xSwitchMacListStatic.1.<vlan_id>.<dec_macaddress>**

Where:

- <dec_macaddress> — MAC address, in a sequence of decimal numbers format.

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xSwitchMacListInterface.1.236.152.222.208.0.205.252
ltp8xSwitchMacListStatic.1.236.152.222.208.0.205.252
```

The command requests the interface and the type of the entry, with a MAC address 98:de:d0:00:cd:fc in 236 VLAN.

4.6 Multicast

See section [IGMP group table](#).

4.7 PPPoE sessions

PPPoE sessions information is available in the *ltp8xOLTPPPoESessionsTable*.

A list of client MAC addresses for sessions can be obtained by the following request.

Command format:

```
snmpwalk -v2c -c <ro_community> <ipaddr> ltp8xOLTPPPoESessionsClientMac.1
```

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xOLTPPPoESessionsClientMac.1
```

The command displays a table of correspondence between client MAC addresses and GPON-PORT/ONT ID.

If you know the information about a particular record in the table, you can request additional data for it (ONT GEM port, PPPoE session ID, PPPoE session duration, ONT port unlock time. ONT port unlock time is not equals to zero in case of blocking when the limit of PPPoE packets is exceeded. The limit value is configured in profile pppoe-ia., ONT serial number):

Command format:

```
snmpget -v2c -c <ro_community> <ipaddr>
ltp8xOLTPPPoESessionsPort.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPPoESessionsSessionID.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPPoESessionsDuration.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPPoESessionsUnblock.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
ltp8xOLTPPPoESessionsSerial.1.<gpon_port>.<ont_id>.6.<dec_client_mac>
```

Where:

- <gpon_port> – port number increased by 1.

Example:

```
snmpget -v2c -c public 192.168.0.1
ltp8xOLTPPPoESessionsPort.1.7.0.6.168.249.75.90.189.124
ltp8xOLTPPPoESessionsSessionID.1.7.0.6.168.249.75.90.189.124
ltp8xOLTPPPoESessionsDuration.1.7.0.6.168.249.75.90.189.124
ltp8xOLTPPPoESessionsUnblock.1.7.0.6.168.249.75.90.189.124
ltp8xOLTPPPoESessionsSerial.1.7.0.6.168.249.75.90.189.124
```

The command displays PPPoE session information for ONT 6/0 with MAC a8:f9:4b:5a:bd:7c.

4.8 Licensing information

Information about the installed license is available in the *ltp8xLicense* table.

Command format:

snmpwalk -v2c -c <ro_community> <ipaddr> ltp8xLicense

Example:

```
snmpwalk -v2c -c public 192.168.0.1 ltp8xLicense
```

The command displays information about the installed license.

5 The list of changes

Document version	Issue date	Firmware version	Revisions
Version 9.4	02.11.2022	3.46.0	Synchronization with firmware version 3.46.0
Version 9.3	13.12.2021	3.44.0	Synchronization with firmware version 3.44.0
Version 9.2	30.11.2021	3.42.2	Synchronization with firmware version 3.42.2
Version 9.1	14.10.2021	3.42.1	Synchronization with firmware version 3.42.1
Version 9.0	31.05.2021	3.42.0	<p>Added sections:</p> <p>PoE management on ONT ports</p> <p>Changed sections:</p> <p>ETH ports state</p>
Version 8.0	28.04.2021	3.40.2	Synchronization with firmware version 3.40.2
Version 7.0	10.12.2020	3.40.0	Synchronization with firmware version 3.40.0
Version 6.0	20.05.2020	3.38.2	Synchronization with firmware version 3.38.2
Version 5.0	07.02.2020	3.38.1	Synchronization with firmware version 3.38.1
Version 4.0	13.12.2019	3.38.0	<p>Synchronization with firmware version 3.38.0</p> <p>Sections added:</p> <ul style="list-style-type: none"> • Service-utilization counters enabling; • Request metrics for service-utilization counters; • Service-utilization counters disabling; • Unknown multicast forwarding enabling.
Version 3.0	08.10.2019	3.36.2	Synchronization with firmware version 3.36.2
Version 2.0	25.02.2019	3.36.0	<p>Commands added:</p> <ul style="list-style-type: none"> • Channel Group configuration; • address-table profiles configuration; • multicast loopback configuration; • display downstream-ber counters for interface.
Version 1.0	03.07.2018	3.32.0	First issue

TECHNICAL SUPPORT

For technical assistance in issues related to operation of Eltex Ltd. equipment, please contact the Service Center.

Feedback form on the website: <https://eltex-co.com/support/>

Servicedesk: <https://servicedesk.eltex-co.ru>

Visit Eltex official website to get the relevant technical documentation and software for Eltex Ltd. equipment:

Official website: <https://eltex-co.com/>

Download center: <https://eltex-co.com/support/downloads>